

## FA008960DVR



**960H**

Support :



iPhone BlackBerry

### Key Features

- Video Input/Output: BNC 8CH In/ 1CH Out/ VGA 1CH Out, HDMI 1CH Out
- Audio Input/Output: RCA 2CH In/ 1CH Out
- Compression Method: H.264
- Hexaplex operation simultaneously: Preview, recording, playback, and network live, backup, playback
- 1 RJ-45 Ethernet connector, Static, Dynamic IP and DDNS , Support Internet Explorer and special client software
- 2 x USB
- Backup: USB2.0 and Network
- Support remote view by Mobilephone

## FA008960DVR-Stand-Alone DVR

<b>Channel</b>	8-channel H.264 Network Digital Video Recorder (8CHx960H)
<b>Video Compression</b>	H.264 PAL/NTSC
<b>Video Input / Output</b>	BNC 8-channel input and 1-channel BNC Output
<b>VGA Output</b>	1 Port VGA Resolution: 1024x768,1280x1024 with 1-channel HDMI output
<b>Audio Input / Output</b>	RCA 1-channel input/ RCA 1-channel output
<b>Display Resolution</b>	960H 960x576 (PAL); 960H 960 x 480 (NTSC)
<b>Display Frame Rate</b>	200fps (PAL);240fps (NTSC) (shared by 8 cameras)
<b>Recording Resolution</b>	960H 960x576 /D1 704 x 576 (PAL); 960H 960 x 480 / /D1 720 x 480 (NTSC)
<b>Playback Resolution</b>	4 x 960H
<b>Hard Disk</b>	1 x SATA Interface Up to 2TB Capacity
<b>Port LAN</b>	RJ-45 Ethernet connector, Support Static, Dynamic IP and Support TCP/IP, PPOE, DHCP, DNS, DDNS, UPNP
<b>Others</b>	Support Internet Explorer, Mobile phone and special client software With Rs485 x 1,2 USB, 1 x IR Controller, 1xUSB2.0 mouse. Support PELCO-P&PELCO-D PTZ control